


Single-color dimmable RF rotary switch for LED lighting - SUNRICHER - Easy RF

Ref. D2805R

SUNRICHER EASY RF series D2805R LED rotary dimmer is a rotary dimmer that offers both switching and smooth brightness dimming functions for single color LED lighting. Designed with sleek and compact appearance, high strength tempered glass material and rotary knob, the LED dimmer offers smooth and precise dimming and switching functions without any flicker. It is quite easy to turn on/off by clicking the rotary knob and dim the brightness by turning the rotary knob. Compatible with RF receivers, which are available in constant voltage and constant current versions, the LED rotary dimmer is capable of controlling different types of LED lighting.* Installation requires a qualified professional and/or advice from our technicians.

Pair with RF receiver (Method 1)



Step 1:
Do wiring the RF receiver according to wiring diagram (please refer to the instruction of RF receiver that you would like to pair with).

Step 2:
Click the "Learning Key" button on RF receiver to set it into pairing status.

Step 3:
Rotate or click the knob, LED lights connected with the RF receiver flicker once means the receiver is paired with the remote successfully.

Note: One receiver can be paired with max 8 remote controls.

Product data

Nominal Voltage (V)	3V-DC
Sensor	Yes
Detection range (m)	25000
Dimensions (mm) LxLxh	86x86x13
Material	Plastic
Use Outdoor	No
IP	IP20
Temperature range	0 ~ +40°C
Frequency of use	Intensive
Lifetime (h)	35000
Energy efficiency class	A+ (2021)
Certificates	CE, ROHS
Warranty	According to legal guarantee: 2 years
Mounting	Recessed
Connectivity	Radiofrequency
Colour control	Monocolor
Number of zones	1

